

## MSD-V6 Modular Audio

# MSD-VAB4D

The MSD-VAB4D is a modular Dante audio option that is factory-installed and supports up to four (4) input and four (4) output audio signals. Stereo pairs (left and right audio channels) can be transmitted to two (2) inputs and two (2) outputs, respectively. The Dante audio output can be switched together with video switching. Multichannel audio is downmixed and output as Dante signals. Dante audio inputs can be embedded over HDMI and then de-embedded as an analog audio output.

### ■ Specification

		MSD-VAB4D
Audio input/output	Dante	1 input/output
		Dante
		Up to 4 input channels, Up to 4 output channels
		Sampling frequency: 44.1/48/88.2*/96 kHz*
		Reference level: -20 dBFS, Max. input/output level: 0 dBFS
		Connector: RJ-45
		Maximum distance: 328 ft. (100 m)
		Cable: CAT.5E HDC, CAT5e (UTP/STP), CAT6 (UTP/STP), CAT6A (UTP/STP)

\*Dante channel: two (2) inputs/two (2) outputs.

### ■ Front & Rear Panels

MSD-V62UC with MSD-VIV1UC and MSD-VAB4D (Option)

